




INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification ⁶ : H04L 7/033	A1	(11) International Publication Number: WO 99/12306 (43) International Publication Date: 11 March 1999 (11.03.99)
(21) International Application Number: PCT/US98/18886 (22) International Filing Date: 4 September 1998 (04.09.98) (30) Priority Data: 60/058,040 4 September 1997 (04.09.97) US (71) Applicant: SILICON IMAGE, INC. [US/US]; 10131 Bubb Road, Cupertino, CA 95014 (US). (72) Inventors: JEONG, Deog-Kyoon; 106-706, Dae-woo-HyoRyong Apt., 1038, Bangbae-3-dongu, Seocho-ku, Seoul 137-063 (KR). AHN, Gijung; 523 Walker Drive #4, Mountain View, CA 94043 (US). (74) Agents: OKAMOTO, James, K. et al.; Fenwick & West LLP, Two Palo Alto Square, Palo Alto, CA 94306 (US).		(81) Designated States: CA, JP, KR, European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE). Published With international search report. Before the expiration of the time limit for amending the claims and to be republished in the event of the receipt of amendments.

(54) Title: SYSTEM AND METHOD FOR HIGH-SPEED, SYNCHRONIZED DATA COMMUNICATION



(57) Abstract

A system for transmission and recovery of original digital data includes an encoder, a transmitter, a receiver, a decoder, and an analog phase locked loop. The analog phase locked loop supplies a sender's clock to the transmitter and a receiver's clock to the receiver, where the sender's clock frequency is a first integer multiple of the system clock frequency, and the receiver's clock frequency is a second integer multiple of the sender's clock frequency within 0.1 % tolerance. In a normal flow situation, data frames are output by the receiver in alternate cycles of the system clock. In an overflow situation, data frames are output by the receiver in consecutive cycles of the system clock. In an underflow situation, data frames are not output by the receiver in consecutive cycles of the system clock.

FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece	ML	Mali	TR	Turkey
BG	Bulgaria	HU	Hungary	MN	Mongolia	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MR	Mauritania	UA	Ukraine
BR	Brazil	IL	Israel	MW	Malawi	UG	Uganda
BY	Belarus	IS	Iceland	MX	Mexico	US	United States of America
CA	Canada	IT	Italy	NE	Niger	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NL	Netherlands	VN	Viet Nam
CG	Congo	KE	Kenya	NO	Norway	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NZ	New Zealand	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	PL	Poland		
CM	Cameroon	KR	Republic of Korea	PT	Portugal		
CN	China	KZ	Kazakhstan	RO	Romania		
CU	Cuba	LC	Saint Lucia	RU	Russian Federation		
CZ	Czech Republic	LI	Liechtenstein	SD	Sudan		
DE	Germany	LK	Sri Lanka	SE	Sweden		
DK	Denmark	LR	Liberia	SG	Singapore		
EE	Estonia						

SYSTEM AND METHOD FOR HIGH-SPEED, SYNCHRONIZED DATA COMMUNICATION

5

BACKGROUND OF THE INVENTION

Technical Field

This invention relates to data communication systems. More particularly, this invention relates to the recovery using oversampling in a receiving system of digital data transmitted via a high-speed link.

10

Description of Related Art

As electronic and computer technology continues to evolve, communication of information among different devices, either situated near by or at a distance becomes increasingly important. For example, it is now more desirable than ever to provide for high speed communications among different chips on a circuit board, different circuit boards in a system, and different systems with each other. It is also increasingly desirable to provide such communications at very high speeds, especially in view of the large amount of data required for data communications in intensive data consuming systems using graphical or video information, multiple input-output channels, local area networks, and the like.

15

It is particularly desirable to enable individual personal computers, workstations, or other computing devices, within which data is normally internally transferred using parallel data buses, to communicate with each other over relatively simple transmission lines. Such transmission lines typically include only one or two conductors, in contrast with the 64-bit and wider data paths within computing systems now commonly available.

20

A communication system that includes oversampling is often utilized to recover data transmitted data. Such a system includes a receiver which samples the incoming serial data stream at a rate greater than the rate at which symbols (bits) are being transmitted. For example, in a three-times (3x) oversampling receiver, the incoming data stream is sampled at a rate

25

order to effectively implement such a receiver when the rate of data transmission is very high.

One problem is the difficulty in handling overflow and/or underflow of incoming data at the receiving end. For example, usually the output of a 3x oversampler contains sets of three consecutive 1s or 0s, but occasionally 4 or 2 consecutive 1s or 0s may occur. Such overflow and/or underflow will occasionally occur, for example, when the frequency of the local clock of the transmission system is not in precise synchronization with the local clock of the receiving system, when there is jitter in the sampling clock, and so on.

Other problems include difficulties in determining the correct symbol (bit) boundaries in the oversampled data stream and difficulties in determining the correct values of the symbols from the multiple samplings of each symbol.

SUMMARY OF THE INVENTION

The above described needs are met and problems are solved by the present invention. A system for transmission and recovery of original digital data includes an encoder, a transmitter, a receiver, a decoder, and an analog phase locked loop. The analog phase locked loop supplies a sender's clock to the transmitter and a receiver's clock to the receiver, where the sender's clock frequency is a first integer multiple of the system clock frequency, and the receiver's clock frequency is a second integer multiple of the sender's clock frequency within 0.1% tolerance. In a normal flow situation, data frames are output by the receiver in alternate cycles of the system clock. In an overflow situation, data frames are output by the receiver in consecutive cycles of the system clock. In an underflow situation, data frames are not output by the receiver in consecutive cycles of the system clock.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a block diagram of a communication system for transmission and recovery of digital data via a communication channel according to a preferred embodiment of the present invention.

Fig. 2 is a block diagram of a transmitter within the communication system according to a preferred embodiment of the present invention.

present invention.

Fig. 4 is a block diagram of an oversampler located in the receiving side of the communication system according to a preferred embodiment of the present invention.

5 Fig. 5 is a timing diagram for the oversampler according to a preferred embodiment of the present invention.

Fig. 6 is a block diagram of a digital phase locked loop (digital PLL) located in the receiving side of the communication system according to a preferred embodiment of the present invention.

10 Fig. 7 is a diagram illustrating the mapping of the oversampled data to groups and phases within the digital PLL according to a preferred embodiment of the present invention.

Fig. 8 is a diagram illustrating an example of data selection within the digital PLL according to a preferred embodiment of the present invention.

15 Fig. 9 is a diagram illustrating the operation of data alignment within the digital PLL according to a preferred embodiment of the present invention.

Fig. 10 is a block diagram of a frame aligner located in the receiving side of the communication system according to a preferred embodiment of the present invention.

Fig. 11 is a diagram illustrating the operation of an aligned FIFO within the frame aligner according to a preferred embodiment of the present invention.

20 Fig. 12 is a timing diagram illustrating the output from the frame aligner according to a preferred embodiment of the present invention.

Fig. 13 is a diagram illustrating the usage of the various bits and ranges of bits in the aligned FIFO within the frame aligner according to a preferred embodiment of the present invention.

25 Fig. 14 is a state diagram of the operation of the frame aligner 110. Four states are shown:

the graph arrows A-H in the state diagram of Fig. 14.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

Overall System

5 Fig. 1 is a block diagram of a communication system for transmission and recovery of digital data via a communication channel 101 according to a preferred embodiment of the present invention. The communication system includes the channel 101, an encoder 102, a transmitter 104, a receiver 105, a decoder 112, and a phase locked loop (PLL) 114. The receiver 105 includes an oversampler 106, a digital PLL 108, and a frame aligner 110.

10 The channel 101 comprises a high-speed point-to-point link in a preferred embodiment of the present invention. Such a link includes a transmission line made from twisted pair, coaxial cable, or some other implementation of the physical layer.

 The encoder 102 receives original data to be transmitted (TX data) from a source (not shown). For example, the original data may be graphics data from a computer for display on a graphics monitor, and the encoder 102 may be embodied within a chip on a graphics card in the computer. In a preferred embodiment, the original data is received in parallel form from the source. The source may, for example, comprise of a graphics processor chip, or a bus of a workstation, server, or personal computer. The encoder 102 encodes the original data in order to make it more suitable for transmission over the channel 101. Such encoding may, for example, transform the data to incorporate error-correction capabilities, minimize transitions in the data to reduce electromagnetic interference, incorporate special signaling (such as synchronization characters), and so on. The encoded data may include more bits than the data before encoding. For example, the data before encoding may be organized in 8-bit frames (bytes). The encoding process may, for example, convert each of those 8-bit frames to 10-bit frames. In other embodiments, different encoding schemes may be employed, such as 8-to-9 bit encoding schemes, or encoding schemes from m bits to n bits. After the data is encoded, the encoder 102 outputs the encoded data to the transmitter 104 for transmission over the channel 101. In a preferred embodiment, the transmitter 104 receives the encoded data in parallel form from the encoder 102 and converts the encoded data from parallel form to serial form for output as an encoded data waveform to the channel 101. In addition, in a preferred embodiment, the transmitter 104 receives a sender's clock signal from the PLL 114 in order to synchronize its

encoded data waveform to the channel 101 in synchronization with the sender's clock signal.

The receiver 105 receives the encoded data waveform from the channel 101. Within the receiver 105, the encoded data waveform is received by the oversampler 106. In a preferred embodiment, the oversampler 106 also receives a receiver's clock signal from the PLL 114 in order to synchronize its operation with that of the transmitter 104. The oversampler 106 obtains an integer multiple number of samples per symbol from the encoded data waveform to generate an oversampled data stream, and so the receiver's clock signal which has a frequency that is an integer multiple of the frequency of the sender's clock signal. In a preferred embodiment, the receiver's clock frequency is three times that of the sender's clock frequency to within a tolerance of 0.1%. For example, if the sender's clock is 100 MHz, then the receiver's clock would be 300 MHz. In other words, on average three samples are obtained per symbol from the encoded data stream. The oversampler 106 outputs the oversampled data stream to the digital PLL 108. The digital PLL 108 receives the oversampled data stream and extracts clock information from edges (data transitions from 1 to 0, or 0 to 1) in the oversampled data stream. In a preferred embodiment, the digital PLL 108 also generates left-aligned data frames and related flag information for output to the frame aligner 110. The frame aligner 110 receives the left-aligned data frames and the related flag information and outputs aligned data frames and output valid signal to the decoder 112. Finally, the decoder 112 receives the aligned data frames and output valid signal and decodes the aligned data frames to regenerate the original data and output the regenerated data as the received data (RX data). In a preferred embodiment, a liquid crystal display (LCD) controller chip receives the RX data from the decoder 112 and has the RX data displayed graphically on the display.

Transmitter

Fig. 2 is a block diagram of a transmitter 104 within the communication system according to a preferred embodiment of the present invention. The transmitter 104 includes a timing aligner 202, a data selector 204, a channel driver 206, and a signal level controller 208.

Fig. 3 is a timing diagram for the transmitter 104 according to a preferred embodiment of the present invention. The signals shown in Fig. 3 include the system clock signal 302, the encoded parallel data signal 304, a first half clock delayed data signal 306, and data selector output signal 308.

receives the encoded parallel data signal 304 from the encoder 102. For purposes of illustration, the encoded parallel data signal 304 in particular includes 10-bit data frames with bits labeled D[0:9]. In this embodiment, the timing aligner 202 delays the last 5 bits of each data frame by
5 half of a system clock cycle to generate the first half clock delayed data signal 306.

The data selector 204 converts the encoded data from parallel to serial form. In this embodiment, both the parallel data signal 304 and the delayed data signal 306 are transferred to the data selector 204. The data selector 204 also receives the sender's clock signal from PLL 114. The frequency of the sender's clock signal in this particular case is ten (10) times the
10 frequency of the system clock signal 302. The data selector output signal 308 is synchronized to the sender's clock signal.

The channel driver 206 receives the data selector output signal 308 and drives that signal onto the channel 101 in the form of an encoded data waveform. Signal level controller 208 controls the strength of the encoded data waveform driven by the channel driver 206.

15 Oversampler

Fig. 4 is a block diagram of an oversampler 106 located in the receiving side of the communication system according to a preferred embodiment of the present invention. The oversampler 106 includes a channel impedance controller 402, a channel amplifier 404, a sampler 406, and a timing aligner 408.

Fig. 5 is a timing diagram for the oversampler 106 according to a preferred embodiment of the present invention. The signals shown in Fig. 5 include the system clock signal 302, sampling timing signal 502, second half clock delayed data signal 504, a series of sample data signals 506-0, 506-1, 506-2, ..., 506-(xn-2), and 506-(xn-1) (where n = the number of bits in a data frame of the encoded data, and x = a multiplier due to the oversampling), and timing
25 aligner output signal 508. In the particular example shown in Fig. 5, n = 10, x = 3 (for 3x oversampling), so xn = 30.

The channel impedance controller 402 allows adjustments to be made to the input impedance of the receiver 105 so that the input impedance matches the channel impedance. The channel amplifier 404 receives the encoded data waveform and amplifies and/or shifts it so that
30 the sampler 406 can better sense the features in the waveform.

amplifier 404 and the receiver's clock signal from the PLL 114. In the particular example illustrated in Fig. 5, the receiver's clock signal would have a frequency 30 times that of the system clock signal. The sampler 406 takes samples of the amplified waveform at a sampling
5 frequency corresponding to the receiver's clock frequency. Thus, in a single system clock cycle, thirty (30) samples are taken in this particular case. These 30 samples are shown as S0 through S29 in the sampling timing signal 502, and the 30 samples correspond to a single oversampled data frame.

For the sampler 406 whose operation is illustrated in Fig. 5, the sampler 406 holds the
10 sampled data for a duration of a half cycle of the system clock 302 and precharges circuits for a duration of the other half cycle. This is illustrated by the series of sample data signals 506-0, 506-1, 506-2, ..., 506-28, and 506-29 in Fig. 5. Therefore, for this sampler 406, it is needed for a device to hold the sampled data for a duration of the other half cycle. Such a device is the timing aligner 408. The timing aligner 408 holds the first half of the oversampled data frame
15 (i.e. the first 15 of the 30 samples in this particular case) for the other half cycle. The timing aligner 408 also synchronizes the entire oversampled data frame and also outputs 508 the entire oversampled data frame beginning at the next cycle of the system clock signal 302.

Digital PLL

Fig. 6 is a block diagram of a digital phase locked loop (digital PLL) 108 located in the
20 receiving side of the communication system according to a preferred embodiment of the present invention. One function of the digital PLL 108 is to extract clock information, such as phase information, from the oversampled data stream 702. The digital PLL 108 includes an edge extractor 602, an edge counter 604, a data select controller 606, a data delay device 608, a data selector 610, a last 1-bit delay 612, and a data left-side aligner 614. Fig. 7 is a diagram
25 illustrating the mapping of an oversampled data stream 702 to groups 706 and phases 704 within the digital PLL 108 according to a preferred embodiment of the present invention.

A current oversampled data stream 702 is received by the data delay device 608. The data delay device 608 holds the current oversampled data stream 702 and makes the current oversampled data stream 702 available to the data selector 610 until the data select controller
30 606 has determined the data selection position. The last 1-bit delay device 612 holds the last bit sample S29 from the previous oversampled data stream 702 and makes the last bit sample S29 available to the data selector 610 until the data select controller 606 has determined the data

device 612 replaces the last bit sample S29 from the previous oversampled data stream 702 with the last bit sample S29 from the current oversampled data stream 702.

Fig. 8 is a diagram illustrating an example of data selection within the digital PLL 108 according to a preferred embodiment of the present invention. A current oversampled data stream 802 is received by the edge extractor 602 from the oversampler 106. The edge extractor 602 determines the locations of data transitions (edges) within the current oversampled data stream 802 and outputs an edge extractor signal 804. The edge extractor signal 804 has a value of one at locations where edges are found and has a value of zero elsewhere (where no edges are found). The edge counter 604 receives the edge extractor signal 804 and determines the phase 806 of any edge in each group of the current oversampled data stream 802. The edge counter 604 counts the number of edges with each phase. For a 3x oversampling system, the edge counter 604 counts the number of edges in phase0 (edge0), phase1 (edge1), and phase2 (edge2). The data select controller 606 uses phase information about the edges from the edge counter 604 to determine a data selection position. For the example shown in Fig. 8, the data selection position is phase2. The data selector 610 uses the data selection position from the data select controller 606 to select a received data stream 812 from the current oversampled data stream 802.

Fig. 9 is a diagram illustrating the operation of data alignment within the digital PLL 108 according to a preferred embodiment of the present invention. The data left-side aligner 614 receives as input 902 the last sample bit 803 [S29] from the last 1-bit delay device 612 and receives the received data stream 812 [D0:D9] from the data select controller 606. In this embodiment, the received data stream 812 comprises 10 bits [D0:D9]. In this embodiment, the data left-side aligner 614 generates as output 904 eleven data bits [Y0:Y10] and 2 flag bits [V9 and V10]. In this embodiment, the eleven data bits and the two flag bits are determined as follows.

If the data selection position 810 for the previous oversampled data stream was phase0 [P0] and the data selection position 810 for the current oversampled data stream 802 is phase2 [P2], then, as shown by line 906, $Y_0 = S_{29}$, $Y_1 = D_0$, $Y_2 = D_1$, $Y_3 = D_2$, $Y_4 = D_3$, ..., $Y_9 = D_8$, and $Y_{10} = D_9$, and $V_9 = V_{10} = 1$. V_9 and V_{10} represent valid bits for data bits Y_9 and Y_{10} , respectively. In this case, V_9 and V_{10} both being one indicates that Y_9 and Y_{10} both hold

bit in the received data stream 812.

On the other hand, if the data selection position 810 for the previous oversampled data stream was phase2 [P2] and the data selection position 810 for the current oversampled data stream 802 is phase0 [P0], then, as shown by line 908, $Y0 = D1$, $Y1 = D2$, ..., $Y7 = D8$, and $Y8 = D9$, and $V9 = V10 = 0$. In this case, $V9$ and $V10$ both being zero indicates that neither $Y9$ nor $Y10$ hold a valid data bit. Furthermore, in this case, $D0$ is discarded in order to remove a duplicated bit in the received data stream 812.

Finally, in other cases that do not fall into the two above-described situations, then, as shown by line 910, $Y0 = D0$, $Y1 = D1$, ..., $Y8 = D8$, and $Y9 = D9$, and $V9 = 1$, and $V10 = 0$. For these cases, $V9$ being one indicates that $Y9$ holds a valid bit, but $V10$ being zero indicates that $Y10$ does not hold a valid bit.

Frame Aligner

Fig. 10 is a block diagram of a frame aligner 110 located in the receiving side of the communication system according to a preferred embodiment of the present invention. The frame aligner 110 includes an aligned FIFO (first in first out) 1002, a data delay 1004, a frame selector 1006, a sync pattern finder 1008, and a frame controller 1010.

Fig. 11 is a diagram illustrating the operation of an aligned FIFO 1002 within the frame aligner 110 according to a preferred embodiment of the present invention. The aligned FIFO 1002 receives the output 904 (including 11 data bits [$Y0:Y10$] and 2 flag bits [$V9$ and $V10$]) from the data left-side aligner 614. In this embodiment, the aligned FIFO 1002 also contains 21 bits of data previously received from the data left-side aligner 614.

In the particular instance illustrated in Fig. 11, the "previous" data in aligned FIFO 1002 is shown in line 1102 and includes the following 32 bits: $A9$; $B0-B9$; $C0-C9$; and $D0-D10$. The "next" data in aligned FIFO 1002 are shown by line 1104 and are designated as the 32 bits $X0-X31$. The contents of the 32 bits $X0-X31$ depend upon the values of the two flag bits [$V9$ and $V10$] accompanying the 11 previous data bits $D0-D10$. If $V9$ and $V10$ were both zero, then $D9$ and $D10$ are not valid, so the next data in aligned FIFO 1002 are shown by line 1106. In this first case, the previous data in the aligned FIFO 1002 are shifted to the left by 9 bit places, and then the last 11 bit places $X21-X31$ are overwritten with newly received 11 data bits $E0-E10$. On the other hand, if $V9 = 1$ and $V10 = 0$, then $D9$ is valid, but $D10$ is not, so the next data in

FIFO 1002 are shifted to the left by 10 bit places, and then the last 11 bit places X21-X31 are overwritten with newly received 11 data bits E0-E10. Finally, if V9 and V10 are both one, then D9 and D10 are both valid, so the next data in aligned FIFO 1002 are shown by line 1110. In this third case, the previous data in the aligned FIFO 1002 are shifted to the left by 11 bit places, and then the last 11 bit places X21-X31 are overwritten with newly received 11 data bits E0-E10.

Fig. 12 is a timing diagram illustrating the output from the frame aligner 110 according to a preferred embodiment of the present invention. Fig. 13 is a diagram illustrating the usage of the various bits and ranges of bits in the aligned FIFO 1002 within the frame aligner 110 according to a preferred embodiment of the present invention.

The contents of the aligned FIFO 1002 are received by both the sync pattern finder 1008 and the data delay device 1004.

The data delay device 1004 selectively delays the contents of the aligned FIFO 1002 depending on the possible overflow or underflow situations. The data delay device 1004 outputs (possibly delayed) X0-X31 to the frame selector 1006. The frame selector 1006 selects a frame for output by the frame aligner 110. The frame is 20 bits wide and begins at a bit pointed to by a frame pointer. The frame pointer must lie within the frame pointer range 1304 of X0 to X10. Since the frame pointer range 1304 is from X0 to X10, and the frame is 20 bits wide, the window 1308 from which a frame may be possibly selected is from X0 to X29.

The sync pattern finder 1008 searches for a synchronization (sync) pattern within the contents of the aligned FIFO 1002. In this embodiment, a frame may be aligned with a single sync pattern which is 10 bits wide. Such an alignment would be desirable if misalignment occurs during communication. Since the frame pointer range 1304 is from X0 to X10, and the sync pattern is 10 bits wide, the window 1306 over which a sync pattern must be search is from X0 to X19.

If a sync pattern is found by the sync pattern finder 1008, then the frame is realigned by the frame controller 1010 sending a signal to have the frame selector 1006 change the frame pointer to a position which is dependent upon the start position of the sync pattern. In addition, the frame controller 1010 sends an output invalid signal to the decoder 112. On the other hand, if a sync pattern is not found, then the frame controller 1010 causes the frame selector 1006 to

addition, the frame controller 1010 sends an output valid signal to the decoder 112 when 20 bits of valid data are ready to be sent to the decoder 112..

The output from the frame aligner 110 is synchronized with the system clock signal
 5 1202. In a normal case 1204, 20 bits of valid data are generated in every other cycle of the system clock. Fig. 12 shows the output valid signal 1204A and the output data signal 1204B by the frame aligner 110 for this normal situation. However, if the clock frequency of the transmitter is higher than that of the receiver, then once in a while an overflow case 1206 occurs. In an overflow case 1206, 20 bits of valid data are generated in two consecutive cycles of the
 10 system clock. Fig. 12 shows the output valid signal 1206A and the output data signal 1206B for this overflow situation. Furthermore, if the clock frequency of the receiver is higher than that of the transmitter, then once in a while an underflow case 1208 occurs. In an underflow case 1208, a delay of two consecutive cycles of the system clock is introduced so that the transmitter may "catch up" to the receiver. Fig. 12 shows the output valid signal 1208A and the output data
 15 signal 1208B for this underflow situation.

Fig. 14 is a state diagram of the operation of the frame aligner 110. Four states are shown: S0 for normal flow and invalid output; S1 for normal flow and valid output; S2 for overflow and valid output; and S3 for underflow and invalid output. Example transitions between states are also shown by the various arrows A to H.

20 Fig. 15 is a table including information regarding the example transitions represented by the graph arrows A-H in the state diagram of Fig. 14. The table includes values for the current flags V9 and V10, the current frame pointer, the next frame pointer, and the next valid bit.

The above description is included to illustrate the operation of the preferred
 embodiments and is not meant to limit the scope of the invention. The scope of the invention is
 25 to be limited only by the following claims. From the above discussion, many variations will be apparent to one skilled in the art that would yet be encompassed by the spirit and scope of the invention. For example, it would be relatively straightforward to extend the technique from 3x oversampling to arbitrary times oversampling.

CLAIMS

What is claimed is:

1. A system for transmission and recovery of original digital data, the system including:
 - 5 (a) an encoder for receiving the original digital data and encoding the original digital data to form encoded data frames, and for outputting the encoded data frames;
 - (b) a transmitter for receiving the encoded data frames, forming an encoded data stream, and transmitting the encoded data stream to a channel;
 - (c) a receiver for receiving the encoded data stream from the channel, the receiver
10 including
 - (1) an oversampler for oversampling the encoded data stream to form an oversampled data stream,
 - (2) a digital phase locked loop for receiving the oversampled data stream, extracting clock information from the oversampled data stream, and generating selected
15 data from the oversampled data stream using the clock information, and
 - (3) a frame aligner for generating encoded data frames using the selected data;
 - (d) an analog phase locked loop for receiving a system clock signal having a system clock frequency, supplying a sender's clock signal having a sender's clock frequency to the transmitter, and supplying a receiver's clock signal having a receiver's clock frequency to the
20 receiver, where the sender's clock frequency is approximately a first integer multiple of the system clock frequency, and where the receiver's clock frequency is approximately a second integer multiple of the sender's clock frequency; and
 - (e) a decoder for receiving the encoded data frames from the frame aligner and for decoding the data frames to recover the original digital data.
- 25 2. The system of claim 1, wherein the receiver's clock frequency is approximately the second integer multiple of the sender's clock frequency with less than 0.1% tolerance.

integer multiple is at least three.

4. The system of claim 1, where the original digital data comprises digital data for display as images on a screen.

5. The system of claim 1, wherein (b) the transmitter includes:

(1) a timing aligner for receiving the encoded data frames in parallel from the encoder and delaying a portion of each of the encoded data frames by a fraction of a cycle of the system clock signal;

(2) a data selector for serializing the encoded data frames to form the encoded data stream which is synchronized with the sender's clock signal; and

(3) a channel driver for driving the encoded data stream to the channel.

6. The system of claim 5, where the fraction of the cycle of the system clock signal is one half of the cycle of the system clock signal.

7. The system of claim 5, further including:

a signal level controller coupled to the channel driver for determining a signal strength at which the channel driver drives the encoded data stream to the channel.

8. The system of claim 5, where the portion each of the encoded data frames is a latter half of each of the encoded data frames.

9. The system of claim 5, where the fraction of the cycle of the system clock signal is one half of the system clock signal.

10. The system of claim 1, wherein (c)(1) the oversampler includes:

(i) a channel amplifier for receiving the encoded data stream from the channel and for amplifying a signal strength of the encoded data stream;

(ii) a sampler for receiving the receiver's clock signal and for oversampling the encoded data stream at the receiver's clock frequency to form samplings in a first number of detect cells, where the first number equals a product of the first integer multiple and the second integer multiple; and

holding the first portion of the samplings while corresponding detect cells are precharged, and for outputting the samplings in parallel to the digital phase locked loop.

11. The system of claim 10, wherein (c)(1) the oversampler further includes:
- 5 (iv) a channel impedance controller for adjusting an input impedance of the receiver at the sender's clock frequency.
12. The system of claim 10, where the first portion of the samplings comprises a first half of the samplings.
13. The system of claim 10, where the first number is at least thirty.
- 10 14. The system of claim 1, wherein (c)(2) the digital PLL includes:
- (i) an edge extractor for generating a signal indicating positions of data transitions in the oversampled data stream; and
- (ii) a data select controller for determining a phase at which to select data from the oversampled data stream.
- 15 15. The system of claim 1 wherein (c)(3) the frame aligner includes:
- (i) a sync pattern finder for determining if the oversampled data stream contains a predetermined sync pattern.
16. The system of claim 1, wherein the receiver normally outputs encoded data frames during alternate cycles of the system clock signal.
- 20 17. The system of claim 16, wherein in an overflow situation, the receiver outputs encoded data frames during two consecutive cycles of the system clock signal.
18. The system of claim 16, wherein in an underflow situation, the receiver refrains from outputting encoded data frames during two consecutive cycles of the system clock signal.
19. A method for high-speed communication of digital data including:

signal, where the sender's clock signal is a first integer multiple of the system clock signal, and the receiver's clock signal is a second integer multiple of the sender's clock signal;

receiving the digital data;

5 encoding the digital data to generate encoded data frames;

forming an encoded data stream from the encoded data frames;

transmitting the encoded data stream to a channel in synchronization with the sender's clock signal;

10 receiving the encoded data stream from the channel in synchronization with the receiver's clock signal;

generating encoded data frames from the encoded data stream; and

decoding the encoded data frames to regenerate the digital data.

20. A method for high-speed communication of digital data including:

15 inputting the digital data to a transmitter, where during each cycle of a system clock signal one predetermined portion of the digital data is input;



transmitting the digital data as a waveform from the transmitter to a channel, where during each cycle of the system clock signal one predetermined portion of the digital data is transmitted.

receiving the waveform from the channel to a receiver;

20 oversampling the waveform to generate an oversampled data stream;

determining the digital data from the oversampled data stream; and

outputting the digital data from the receiver, where normally two predetermined portions of the digital data are output during each alternate cycle of the system clock signal, where for overflow situations the digital data is output during consecutive cycles of the system clock, and
25 where for underflow situations no digital data is output during consecutive cycles of the system clock.



2/11




FIG. 3






FIG. 4



FIG. 7



5/11

**FIG. 6**







FIG. 8

7/11



8/11

**FIG. 10****FIG. 13**

9/11

1102	PREVIOUS DATA IN "ALIGNED FIFO"									
	A9	B0	B9	C0	C9	D0	D10	Y0	Y10	

NEXT DATA IN "ALIGNED FIFO"

FIG. 11

1104	FLAG											
	V9	V10	X0	X1	X10	X11	X20	X21	X31			
1106			B8	B9	C0	C8	C9	D0	D8	E0	E10	
	0	0										
1108			B9	C0	C9	D0	D9	E0	E10			
	1	0										
1110			C0	C1	D9	D0	D1	D10	E0	E10		
	1	1										

10/11





FIG. 12

11/11

**FIG. 14**

Graph Arrow	Current Flags		Current Frame Pointer	Next Frame Pointer	Next Valid Bit
	V9	V10			
A	0	0	$X[n]$	$X[n+1]$	1
	1	0		$X[n]$	1
	1	1		$X[n-1]$	1
B	0	0	$X[n]$	$X[n+1]$	0
	1	0		$X[n]$	0
	1	1		$X[n-1]$	0
C	1	1	$X[1]$	$X[0]$	1
D	1	0	$X[10]$	$X[1]$	1
E	0	0	$X[1]$	$X[1]$	0
F	1	0	$X[10]$	$X[1]$	0
G	0	0	$X[10]$	$X[1]$	0
H	1	1	$X[0]$	$X[10]$	1

FIG. 15

INTERNATIONAL SEARCH REPORT

Int. Application No

PCT/US 98/18886

A. CLASSIFICATION OF SUBJECT MATTER
IPC 6 H04L/033

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 6 H04L

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	LEE K ET AL: "A CMOS SERIAL LINK FOR FULLY DUPLEXED DATA COMMUNICATION" IEICE TRANSACTIONS ON ELECTRONICS, vol. E78-C, no. 6, June 1995, pages 601-611, XP000524416 see page 601, column 2, line 4 - line 19 see page 601, column 2, line 27 - page 602, column 1, line 10 see page 605, column 1, line 18 - line 20 see page 605, column 2, line 18 - line 19 see figure 14	1-3,19
P,X	WO 97 42731 A (SILICON IMAGE INC) 13 November 1997 *abstract*	1-3,19
A	EP 0 498 064 A (IBM) 12 August 1992 see page 1, line 4 - page 2, line 37	1-20

-/--

☒ Further documents are listed in the continuation of box C.

☒ Patent family members are listed in annex.

* Special categories of cited documents :

"A" document defining the general state of the art which is not considered to be of particular relevance

"E" earlier document but published on or after the international filing date

"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

"O" document referring to an oral disclosure, use, exhibition or other means

"P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.

"&" document member of the same patent family

Date of the actual completion of the international search

21 December 1998

Date of mailing of the international search report

05/01/1999

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040, Tx. 31 651 epo nl,
Fax: (+31-70) 340-3016

Authorized officer

Van den Berg, J.G.J.

INTERNATIONAL SEARCH REPORT

Int nal Application No PCT/US 98/18886
--

C.(Continuation) DOCUMENTS CONSIDERED TO BE RELEVANT		
Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	US 4 672 639 A (TANABE TOSHIYUKI ET AL) 9 June 1987 * abstract * <div style="text-align: center; margin-top: 10px;">-----</div>	1-20

INTERNATIONAL SEARCH REPORT

Information on patent family members

International Application No

PCT/US 98/18886

Patent document cited in search report		Publication date	Patent family member(s)	Publication date
WO 9742731	A	13-11-1997	AU 2823697 A	26-11-1997
			US 5835498 A	10-11-1998
EP 0498064	A	12-08-1992	US 5212716 A	18-05-1993
			JP 4320109 A	10-11-1992
US 4672639	A	09-06-1987	JP 1764351 C	28-05-1993
			JP 4053152 B	25-08-1992
			JP 60248086 A	07-12-1985
			JP 1764352 C	28-05-1993
			JP 4053153 B	25-08-1992
			JP 60248087 A	07-12-1985
			JP 1738528 C	26-02-1993
			JP 4023877 B	23-04-1992
			JP 60248088 A	07-12-1985
			CA 1252156 A	04-04-1989
			EP 0165498 A	27-12-1985